# **DVNX Upgrade to Firmware Version 2.2.0**

# **IMPORTANT! 2.2.0 Firmware is ONLY for DVNX units. If** you have a DV2T or DV3T please download the appropriate firmware.

#### These are instructions for upgrading to DVNX Firmware Version 2.2.0. Check Firmware Version.

Download Firmware Version 2.2.0 and run the executable file.


Depending on the browser you are using and your security settings, you may get a few warning screens about downloading exe files from the internet. You should save the file to your computer (usually it defaults to a downloads directory, this is fine). After you have downloaded the file, you will be prompted to run, go ahead, and run it from the browser.

#### The following image is an example of what you might see if you are running Microsoft Edge: See red circle.




Note: if you are running Chrome, Firefox, or Explorer, you will see different warnings. <u>See Other</u> <u>Warnings</u>.


Have a USB stick handy, you will need it for the next few steps. Plug your USB stick into your computer and click yes: See red circle.




#### Click Next to continue: See red circle.



#### Click Yes to acknowledge you have read the license agreement: See red circle.





< Back

Next >

Cancel

## Choose top level of USB stick to save the files. Click OK: See red circles.

Browse For Folder	$\times$
Please select the destination folder:	
> 🏥 Local Disk (C;)	^
USB Drive (D:)	
> ctxapp_130	
devlog	
> DV_Sim_1_4_0	
DV_Sim_2_1_6	
> DV1	~
Make New Folder OK Cancel	

## Click Next to extract: See red circle.


Chex itext to extract. See ited there.	
DVNX Firmware Upgrade 2.2.0	$\times$
Destination Folder for Files	Δ
Please select the destination folder where the package should extract the files:	BROOKFIELD
Please select the destination folder:	
D:\	Browse
$\sim$	
DVNX Firmware Archive < Back Next >	Cancel

	fractica to your CDD site	110
oww DVNX Firmware Upgrade 2.2.0		×
<b>Unpacking Files</b> Please wait while the package files are being ex	xtracted onto your computer	BROOKFIELD
Extracting README.txt		
DVNX Firmware Archive	< <u>B</u> ack <u>N</u> ext >	<u>C</u> ancel

#### Wait for files to be extracted to your USB stick.

#### Click Next to continue: See red circle.

Click Next to continue: See red circle.			
DVNX Firmware Upgrade 2.2.0	$\times$		
<b>Readme Information</b> Please read the following important information:	BROOKFIELD AMETEK		
======================================	^		
Check your DVNX firmware version:			
From the main menu, touch on the Settings Icon (top right). Choose "Device Setup" and then "About".			
IMPORTANT! If Firmware is lower than 2.1.0, you CANNOT upgrade to 2.2.0. Please download the latest DV2T/DV3T firmware instead.			
If you have Firmware 2.1.0 or higher, follow the below directions.			
Upgrading from DVNX Firmware Version 2.1.X to 2.2.0	~		
DVNX Firmware Archive < Back Next >	Cancel		




Plug your USB stick into the back of the DVNX instrument: See red/pink circle.



Touch the Settings Icon: See red circle.

An example is shown here on the top right of the Configure Viscosity Test screen.



## Touch Admin Functions: See red circle.

12 1:2	23 P <b>M</b>	06/26/15	
$\bigcirc$	Sett	ings	
Device Setup			>
User Settings			>
Global Settings			>
Admin Functions			


Touch Update Software: See red circle.

+ C+++++++++++++++++++++++++++++++++++	
Admin Functions	
Log In and Lock Out	>
Electronic Signatures	>
Users and Access	>
Manage Settings	>
Manage Data	>
Update Software	

**IMPORTANT! 2.2.0 Firmware is ONLY for DVNX units. If** you have a DV2T or DV3T please download the appropriate firmware. Touch the USB folder that has the upgrade files: See red circle.



Touch DVNX\_ONLY\_2\_0\_2\_4\_S.txt: See red circle.




#### Touch OK: See red circle.



Wait for the upgrade to complete. This may take a while.

# Do not unplug the USB or turn off the instrument!



Click OK. Reboot instrument.

(Turn off the instrument; wait a couple seconds then turn it back on): See red circle.




# **Check Firmware Version**

Touch the Settings Icon: see red circle.

An example is shown here on the top right of the Configure Viscosity Test screen.

1:21 PM	06/26/15 🔬		
Configure Viscosity Test Q			
Unsaved Test			
Step 1 of 2 🔰	Torque 6.2 %		
Spindle	Speed		
CP-41(41) 🔰	8.0 RPM		
Temperature	End Condition		
Live 24.0 °C Set 25.0 °C	00:00: 10 🔰		


Touch Device Setup: see red circle.



Touch About: see red circle.

1 2 3 PM 06/26/15	
C Device Setup	
Temperature	>
Printer Setup	>
Auto Zero	>
Oscillation Check	>
Technical Support Info	>
About	

Take note of which Firmware Version your instrument is running. See red circle.



**Return to Instructions** 

# Warnings and Pop-up Messages

## **Microsoft Edge**

An example of what you might see if you are running Microsoft Edge: See red circle.



### **Chrome** An example of what you might see if you are running Chrome: See red circles.

0	This type of file can harm yo Do you want to keep DVNX2	Keep Discard
212	VX DVNX220.exe	Open Always open files of this type Show in folder Cancel

## **Firefox** An example of what you might see if you are running Firefox: See red circles.

Opening DVNX216.exe	$\times$
You have chosen to open:	
DVNX220.exe	
which is: exe File (8.6 MB)	
from: C:\Users\ktopham\Desktop\DVT\web_new\	
Would you like to save this file?	
Save File Cancel	

ڬ Enter name of file to save to			×
$\leftarrow$ $\rightarrow$ $\checkmark$ $\Uparrow$ $\clubsuit$ > This PC > Downloads	~	ت ب Sea	arch Downloads
Organize 🔻 New folder			≣≡ ▾ (?)
<ul> <li>✓ A Quick access</li> <li>▲ Name</li> <li>▲ Desktop</li> <li>▲ Downloads</li> </ul>	No items match	Date modified your search.	Туре
<ul> <li>Documents ★</li> <li>Pictures ★ &lt;</li> </ul>			
File name: DVNX220.exe Save as type: exe File (*.exe)			~
∧ Hide Folders		Sav	/e Cancel
vrary   Ac   M Inbox (809) - pr   9 Recent up Search DVNX220.exe: Open File	date: G Google	/C:/Users/ ↓    \ [	

**<u>Return to Instructions</u>**